





#### APPLICATION NOTE

# Motor starting and protection for premium-efficiency motors

IE3 / IE4 ready for premium-efficiency motor starting and the new AC-3e utilization category





## International motor efficiency

World industry and commerce are facing an energy challenge. Global demand for energy is rising steadily. At the same time, pressures to reduce energy consumption and carbon dioxide (CO<sub>2</sub>) emissions and provide secure power supplies are becoming ever stronger.

Efficient motors help cut energy costs and limit carbon dioxide emissions. It has been estimated that electric motors account for about 70 percent of the electricity consumed in industrial applications, so the energy saving potential for industries is enormous. Energy consumption depends on the motor's kW rating, the dimensioning of the application and the operating hours. High-efficiency motors can thus play a significant role in reducing  $CO_2$  emissions.

ABB is a long-standing advocate of the need for high efficiency in motors. Its policy is to offer highefficiency motors as standard, available directly from stock. However, instead of concentrating solely on efficiency, we take a lifecycle approach, seeking to minimize the costs associated with our products throughout their lifetime.





ABB is a pioneering technology leader in electrification products, robotics and motion, and industrial automation, serving customers in utilities, industry, and transport and infrastructure globally. Continuing a history of innovation spanning more than 130 years, ABB today is writing the future of industrial digitalization with two clear value propositions: bringing electricity from any power plant to any plug and automating industries from natural resources to finished products.

This application note is written as a general guide for people working with low-voltage switchgear and controlgear applications for high-efficiency motor applications. All these are relevant for IEC-based European applications.

ABB is constantly monitoring the changes in the market for electrical motors to ensure timely adaptation of relevant products to meet the requirements of the latest high-efficiency motor generations.

ABB participates in IEC working groups and IEC high-efficiency motor task forces, which are working on updating relevant product standards for motor starters.

ABB's portfolio matches the latest requirements for IE3 and IE4 motor applications, including the latest utilization categories AC-3 upgrade and AC-3e creation for contactors and motor starters. In particular, ABB has validated coordination solutions for AC-3 and AC-3e applications. The results of these tests can be found in ABB's motor coordination tables.

All the information provided in this application note is only general and each application must be handled as a specific case. Be sure to always follow all national and local installation regulations/ codes for your specific application.



Intro	International motor efficiency	ABB and efficiency	Coordination	Marketing	g Glossary	4 / 31
	standards and regulations	standards		material and	web	
			• • • • • • • • • • • • • • • • • • • •			

- Minimum Energy
   Efficiency classes Performance Standards
  - of line operated AC motors IEC 60034-30-1
- What distinguishes an IE3/IE4 motor from less efficient motors?
- N/H and NE/HE
   EU European motor design Union categories

Regulation 2019/1781

Contact Us @



## International motor efficiency standards and regulations



Figure 1: International motor efficiency standards and regulations.

Since the validation of IEC 60034-30:2008 and its refined IEC 60034-30-1:2014 version, a worldwide energy efficiency classification system has existed for low voltage three-phase asynchronous motors. These international standards have also been created to enable and increase the harmonization of efficiency regulations around the world.

IEC 60034-30-1:2014 defines International Efficiency (IE) classes for single-speed, three-phase, 50 Hz and 60 Hz induction motors. The efficiency levels defined in IEC 60034-30-1 are based on the test method specified in IEC 60034-2-1:2014. Both standards are part of an effort to unify motor testing procedures with Canadian and American standards, and efficiency and product labeling (IE) requirements to enable motor purchasers worldwide to easily recognize premium efficiency products.

To promote market transparency, IEC 60034-30-1 states that both the efficiency class and efficiency value must be shown on the motor rating plate and in the product documentation. The documentation must indicate the efficiency class testing method used because different methods can produce different results.



ntro	o International motor efficiency		ABB and efficiency	Coordination	Marketing	g Glossary	5	
	standards a	and regulations	standards		material and web			
		Efficiency classes		ishas NU/UL				

- Minimum Energy
   Efficiency classes Performance **Standards**
- of line operated AC motors IEC 60034-30-1
- What distinguishes an IE3/IE4 motor from less efficient motors?
- N/H and NE/HE
   EU European motor design Union categories Regulation 2019/1781



/ 31



## **Minimum Energy Performance Standards**

While IEC as an international standardization organization sets guidelines for motor testing and efficiency classes, the organization does not regulate countries' efficiency levels. The biggest drivers for mandatory Minimum Energy Performance Standard (MEPS) levels for electric motors are global climate change, government targets for curbing CO<sub>2</sub> emissions, and growing electricity demand, especially in developing countries. The entire value chain, from the manufacturer to the end-user, must be aware of the legislation to meet local requirements, save energy and reduce the carbon footprint.

Harmonized global standards and the increasing adoption of MEPS around the world are good news for all of us. However, it is important to remember that harmonization is an ongoing process. Although MEPS are already in effect in several regions and countries, they are evolving and differ in scope and requirements. At the same time, more countries are planning to adopt their own MEPS regulations. The world map above shows the existing and future MEPS regulations.



- Minimum Energy · Effic Performance of lin Standards AC n
- Efficiency classes of line operated AC motors IEC 60034-30-1
- What distinguishes an IE3/IE4 motor from less efficient motors?
- N/H and NE/HE EU European motor design Union categories Regulation 2019/1781

an I



6/31



## Efficiency classes of line operated AC motors IEC 60034-30-1

It is important to know which motor types are exempt from the new efficiency regulations. IEC-60034-30-1 defines four International Efficiency (IE) classes for single speed electric motors that are rated as designed for operation on sinusoidal voltage:

- IE4 = Super premium efficiency
- IE3 = Premium efficiency
- IE2 = High efficiency
- IE1 = Standard efficiency

IEC 60034-30-1 covers the power range from 0.12 kW up to 1000 kW. Most of the different technical constructions of electric motors are covered as long as they are rated for direct on-line operation. The coverage of the standard includes the recommendation and exclusions below:

IE3/IE4 motor requirements and recommendation	IE3/IE4 motor exclusion
<ul> <li>Voltage range for low voltage motors up to 1000 V</li> </ul>	• Motors for one speed with 10 or more poles, as well as
<ul> <li>Mains frequency of 50 and 60 Hz</li> </ul>	motors designed for several speeds
• Number of poles: 2, 4, 6, 8	Motors with mechanical commutators
Degree of protection: all	(e.g. DC motors)
• Operating mode: S1 (continuous load), as well as	<ul> <li>Motors that are fully integrated into a machine and can- not be tested independently</li> </ul>
but which can still be operated continuously at rated power	<ul> <li>Motors with integrated frequency inverters (compact drives)</li> </ul>
<ul> <li>Motors with two switchable rated voltages (as long as the magnetic flux is the same at both voltages)</li> </ul>	<ul> <li>Submersible motors that are especially designed to be operated completely immersed in liquids</li> </ul>
• Temperature range: -20°C to +60°C	<ul> <li>Explosion-proof motors and brake motors</li> </ul>
<ul> <li>Installation altitude: up to 4,000 m above sea level</li> </ul>	

Note : Additional exclusions are also provided by the European MEPS (EC 640/2009).

BB	Intro Internation standards	al motor efficiency A and regulations	BB and efficiency Coord standards	ination Marketir material and	ng Glossary d web	7 / 31
	• Minimum Energy Performance Standards	• Efficiency classes of line operated AC motors IEC 60034-30-1	• What distinguishes an IE3/IE4 motor from less efficient motors?	• N/H and NE/HE motor design categories	• EU European Union Regulation 2019/1781	Contact Us

000

# What distinguishes an IE3/IE4 motor from less efficient motors?

IE3/IE4 motors can achieve higher efficiency thanks to innovative design and the use of better conducting material. The higher efficiency design ultimately shows a lower rated motor current for any given kW rating. However, during the motor's starting phase, there may be an increase in inrush and starting current. The increased inrush and starting current can in some cases affect the selection of the starter components as well as the short-circuit protection device.



Figure 2: Overview of the nominal efficiency limits defined in IEC 60034-30-1

Note: See appendix for a detailed overview of the nominal efficiency limits defined in accordance with IEC 60034-30-1.

	ntro Internationa standards	l motor efficiency Al and regulations	BB and efficiency Coord standards	ination Marketin material and	g Glossary web	8 / 31
1 -     	1inimum Energy Performance Standards	• Efficiency classes of line operated AC motors IEC 60034-30-1	• What distinguishes an IE3/IE4 motor from less efficient motors?	<ul> <li>N/H and NE/HE motor design categories</li> </ul>	• EU European Union Regulation 2019/1781	Contact Us @

000

If a motor is directly connected to the power line, the current drawn (which is mostly reactive) will be very high during start-up. The curve in the following graph shows a typical starting RMS current curve for an IE3/IE4 motor in a direct-on-line connection. In general, the motor draws current in three steps:

 After starting, during the first 10 ms to 15 ms: 'Ipeak', an inrush current with a very high peak current. This high peak current is much higher than for IE1/IE2 motors.
 This is a result of the higher locked rotor apparent power and the locked rotor current reaching

This is a result of the higher locked rotor apparent power and the locked rotor current reaching the higher efficiency class according to IEC 60034-30-1.

- Between the inrush and 0.5 s to 10 s, the important step starts (depending on rated power and inertia), there is a locked rotor current 'I lrc'. This effective current remains almost constant until the rotor starts to revolve.
- Typically when the motor starts revolving, the motor current reduced down to motor rated current In, until the motor has reached full speed. Its duration depends on the motor load and design.



Figure 3: Diagram with the current at the start-up of an IE3/IE4 motor.

The tests and analyzes clearly show that high-efficiency motors IE3/IE4 NE/HE, in general, may draw a higher starting current than IE3/IE4 N/H motors.

Once the IE3/IE4 motor reaches full speed, the rated motor current is lower compared to IE2 motors for the same load conditions, because of the higher efficiency (and therefore saving more energy).



Figure 4: Diagram showing the different currents for the IE4/IE3 motors.



ntro	International motor efficiency	ABB and efficiency	Coordination	Marketing	Glossary
	standards and regulations	standards			
					_

- Minimum Energy 
   Efficiency classes Performance Standards
- of line operated AC motors IEC 60034-30-1
- What distinguishes an IE3/IE4 motor from less efficient motors?
- N/H and NE/HE
   EU European motor design Union categories Regulation 2019/1781



9/31



## N/H and NE/HE motor design categories

IEC 60034-12 specifies parameters for the starting performance of single-speed three-phase 50 Hz or 60 Hz cage induction motor designs; the rated voltage is up to 1000 V. The application is directon-line or star-delta starting and a S1 duty type.

However the important part of IEC 60034-12 specifies the design letter E for extended efficiency motors, and additionally describes the new NE and HE designs. The design categories are N/H and NE/HE motor designs, and a description of what this means is shown in the below table:

Motor Design	Specification of the different designs	Specification details	Maximum values of rotor apparen	f locked t power		
			P <sub>N</sub> Range of rated output (kW)	SI/PN		
Design N	Normal starting torque	Normal starting torque three-	PN ≤ 0,4	22		
		phase cage induction motors, intended for direct-on-line	0.4 < PN ≤ 0,63	19		
Design N Design H Design NE		starting, having 2, 4, 6, or 8	0.63 < PN ≤ 1,0	17		
		poles, rated from 0.12 kW to 1600 kW.	1.0 < PN ≤ 1,8	15		
			1.8 < PN ≤ 4,0	14		
Design <mark>H</mark>	High starting torque	High starting torque three-	An example of the e	13		
5		phase cage induction motors with 4, 6 or 8 poles, intended for	6.3 < PN ≤ 25	12		
		directon-line starting, rated	25 < PN ≤ 63	11		
		from 0.12 kW to 160 kW.	63 < PN ≤ 630	10		
 Design <mark>NE</mark>	Normal starting torque +	Normal starting torque three-	PN ≤ 0,4	22		
	Motors utilizing extended / higher locked rotor apparent	orque Normal starting torque three- phase cage induction motors, intended for direct-on-line starting, having 2, 4, 6, or 8 poles, rated from 0.12 kW to 1600 kW. que High starting torque three- phase cage induction motors with 4, 6 or 8 poles, intended for directon-line starting, rated from 0.12 kW to 160 kW. 630 < PN ≤ orque + Normal starting torque three- phase cage induction motors having higher locked rotor t to achieve a class intended for direct-on-line 50034-30-1 starting torque three- phase cage induction motors having higher locked rotor t to achieve a class with 4, 6 or 8 poles, intended for directon-line starting, having 2, 4, 6 or 8 poles, rated from 0.12 kW to 1600 kW.	0.4 < PN ≤ 0,63	19		
	Normal starting torqueNormal starting torque the phase cage induction mot intended for direct-on-line starting, having 2, 4, 6, or 2 poles, rated from 0.12 kW 1600 kW.High starting torqueHigh starting torque three phase cage induction mot with 4, 6 or 8 poles, intend directon-line starting, rate from 0.12 kW to 160 kW.Normal starting torque + Motors utilizing extended / higher locked rotor apparent power and current to achieve a higher Efficiency class according to IEC 60034-30-1Normal starting torque the phase cage induction mot with 4, 6 or 8 poles, intend directon-line starting, having 2, 4, 6 or 8 poles, rated from 0.12 kW to 160 kW.High starting torque + Motors utilizing extended / higher locked rotor apparent power and current to achieve a higher Efficiency class according to IEC 60034-30-1High starting torque three phase cage induction mot having higher locked rotor apparent power than desi with 4, 6 or 8 poles, intend direct-online starting, rate from 0.12 kW to 160 kW	apparent power than design N,	0.63 < PN ≤ 1,0	17		
	higher Efficiency class according to IEC 60034-30-1	intended for direct-on-line starting, having 2, 4, 6 or 8	1.0 < PN ≤ 6,3	15		
	, see a georgeone and a second	poles, rated from 0.12 kW to 1600 kW.	6.3 < PN ≤ 25	14		
Design <mark>HE</mark>	High starting torque +	High starting torque three-	25 < PN ≤ 63	13		
	Motors utilizing extended / higher locked rotor apparent	phase cage induction motors having higher locked rotor	63 < PN ≤ 630	12		
	power and current to achieve a higher Efficiency class according to IEC 60034-30-1	apparent power than design H, with 4, 6 or 8 poles, intended for direct-online starting, rated from 0.12 kW to 160 kW.	630 < PN ≤ 1 600	11		

Note: The locked rotor apparent power shall not be greater than the appropriate value given in the table.

The values given in the table are independent of the number of poles and are maximum values at rated voltage.



Intro	International motor efficiency	ABB and efficiency	Coordination	Marketing	Glossary	10 / 31
	standards and regulations	standards		material and w	eb	

- Minimum Energy 
   Efficiency classes Performance Standards
- of line operated AC motors IEC 60034-30-1
- What distinguishes an IE3/IE4 motor from less efficient motors?
- N/H and NE/HE EU European motor design Union categories Regulation 2019/1781



## EU European Union Regulation 2019/1781

Since 01.07.2021, all three-phase motors in the power range from 750 W to 1 MW that are placed on the market or put into operation within the EU must comply with motor efficiency class IE3 or higher IE4. The regulation aims to sustainably reduce energy consumption. The approximately 8 billion electric motors in use in the EU consume almost half of the electricity generated there. (Source: European Commission).

Three-phase motors	Year of implementa	Year of implementation of minimum requirements							
for continuous operation up to 1000V 50/60Hz, direct online start	From 01.2017	From 07.2021	From 07.2023						
Power	2-, 4-, 6- pole	2-, 4-, 6-, 8- pole	2-, 4-, 6-, 8- pole						
≥ 0.12 < 0.75 kW	-	IE 2	IE 2						
≥ 0.75 < 75 kW	IE 3	IE 3	IE 3						
≥ 75 ≤ 200 kW	IE 3	IE 3	IE 4 (2-, 4-, 6-pole)						
≥ 200 ≤ 375 kW	IE 3	IE 3	IE 3						
≥ 375 ≤ 1000 kW	-	IE 3	IE 3						

#### **Requirements outside the European Union**

European countries that are not members of the EU have incorporated all or most of the EU Directives and regulations into their legislation. Thus, the CE (Conformity Europeene) mark is recognized in these countries.

- EEA & EFTA countries: Iceland, Liechtenstein, and Norway.
- Switzerland, AGA (Agreement on Mutual Recognition) between Switzerland and the EU.
- Turkey via customs union agreement SGM-2019/1781/AB & SGM: 2021/16.
- The UK (United Kingdom) is an exception: regulations and the UKCA (UK Conformity Assessed) mark are to be used from 2023/01 onwards.



and control devices

• Selecting the right combination of protection • Softstarters with premium-efficiency motors

Contact Us @



## ABB and efficiency standards

### ABB determines efficiency values according to IEC 60034-2-1 using the low uncertainty method with additional load losses determined by the method of residual loss.

It is good to mention and emphasize that the IEC 60034-2-1 test method, which is known as an indirect method, is technically equivalent to the test methods in the CSA 390-10 standards and IEEE 112 Method B leading to equivalent losses and therefore efficiency values.

ABB offers a large range of motors, contactors, and manual motor starters. It has long advocated the need for motor efficiency, and high-efficiency products have formed the core of its' portfolio for many years.

ABB supplies high-efficiency motors for additional energy savings when using utilization categories AC-3 and AC-3e defined according to IEC 60947-4-1.

IEC 60947-4-1 Ed.4 introduces a new AC-3e utilization category for AC current switching, keeping the use and definition of the existing AC-3 utilization category unchanged.

AC-3	AC-3e
Refers to the <b>asynchronous</b> motors of designs N and H according to IEC 60034-12:2016.	Refers to <b>asynchronous motors of designs NE and HE</b> , according to IEC 60034-12, with extended / higher locked rotor apparent power and current than designs N and H respectively, to achieve a higher efficiency class according to IEC 60034-30-1.
The AC-3 category remains with unchanged characteristics for the complete control and motor protection product scope defined for motor starting and protection solutions.	<ul> <li>Manual motor starters, 3-pole AF contactors and B mini-contactors are suitable for AC-3e applications.</li> <li>The manual motor starters MS116, MS132, MS165, and the contactors AF09</li> <li>AF190, B6/B7 have an AC-3e rating (same as AC-3 rating): <ul> <li>listed on their respective technical data pages.</li> <li>certified on CB certificates delivered by third-party laboratories.</li> <li>marked on their type label.</li> </ul> </li> <li>For AF205AF1650 contactors, please consult your ABB local sales organization</li> </ul>
AC-3 making and breaking capacities unchanged	New AC-3e making and breaking capacities

#### Squirrel-cage motors starting, switching off motors during running, reversing



and control devices

Contact Us @



# Selecting the right combination of protection and control devices

Short-circuit detection is intended to protect electrical systems against fault currents. The value for the magnetic tripping current should be above the currents caused by a motor during start-up (inrush current and locked rotor current). An electrical system's design is influenced by the level of the response value (magnetic tripping current, overload release current and make/ break current): the higher the response value is, the larger the cable cross-sections that need to be protected. This increases system and switchgear costs. The response values of ABB's protection and control devices have been adapted to meet the requirements of the latest motor generations.

Here is an example using a manual motor starter and a contactor in a motor application:



Figure 5.1: Diagram showing a typical starting current and the characteristics of the protective devices. \*The manufacturer's tolerances must also be considered.



 Intro
 International motor efficiency
 ABB and efficiency
 Coordination
 Marketing
 Glossary

 standards and regulations
 standards
 material and web

 • Selecting the right combination of protection
 • Softstarters with premium-efficiency motors and control devices

13 / 31

Contact Us @

Here is an example using a fuse, a contactor and an overload relay in a motor application:



Figure 5.2: Diagram showing a typical starting current and the characteristics of the protective devices. \*The manufacturer's tolerances must also be considered.



• Selecting the right combination of protection • Softstarters with premium-efficiency motors and control devices

Contact Us @



### Manual motor starters and overload relays

## The advantage of the new, more efficient motors (IE3/IE4) is that the current at the end speed is reduced, resulting in lower energy consumption. The disadvantage is that start-up and inrush currents are significantly higher on average than with previous motor generations.

The ratio, Is/In starting current to nominal current, is increased. Motors with high starting currents can thus cause the manual motor starters (magnetic tripping). This leads to unintentional tripping ("nuisance tripping") during motor start-up.

For example, nuisance tripping can occur if the motor current is in the upper range of the manual motor starter's settings range, and a motor with a high in-rush current is used.

The risk of unwanted tripping increases with the ratio Is/In. The theoretical case of a manual motor starter and thermal overload relays is shown in the figure below. The grey curve shows the startup current of an IE2 motor, the red curve of an IE3 motor. If the values between the motor starting current and the device threshold black curve are too close (when using the IE2 configuration for an IE3 application) it can lead to unwanted tripping.



Figure 6: Diagram showing possibilities for an unexpected tripping

Unwanted tripping can depend on motor technology, correct installation, electrical wiring, equipment, and devices. However, to select the correct manual motor starter and the correct overload relay, you should:

- Ensure that the electrical characteristics specified by the motor manufacturer match those of the motor starters used.
- First, check the motor classification (N/E or NE/HE) or the Is/In ratio. Then select the starter components using the ABB Selected Optimized Coordination tool (SOC, see Chapter 3) providing the relevent motor data (power, voltage, type of short-circuit protection, type of overload protection).
- Follow the motor protection manufacturer's recommendations.
- Note that for NE/HE motors AC-3e rated components must be used.
- Check the max. cable length to the motor and be sure to consider the increased starting currents when selecting the cables.
- Check the switching frequency (operations per hour), as this may increase the component's temperature incorrectly.



Intro International motor efficiency ABB and efficiency Coordination Marketing Glossary standards and regulations standards material and web

• Selecting the right combination of protection • Softstarters with premium-efficiency motors and control devices

15 / 31

Contact Us @



To enable premium efficiency motors to start, ABB has increased the magnetic tripping level for some manual motor starters to ensure a start without tripping. The implementation became effective in August 2014 with IE3 motors.

ABB manual motor starters and thermal overload relays have been subjected to magnetic, electrical, and thermal endurance tests under laboratory conditions to ensure compatibility with IE3 and IE4 motors.





• Selecting the right combination of protection • Softstarters with premium-efficiency motors and control devices

Contact Us 💿



### Contactors

A contactor is an electromechanical device intended to control motors with ON / OFF switching. The rated nominal current of a contactor is specified as In.

ABB's AF contactors have been designed from the outset to handle premium (IE3) and super premium efficiency (IE4) motors. When designing contactors to match the new efficient motors, there is a balance between being able to close the contacts during a high inrush current peak and not causing an increased mechanical tear in the contact system at the same time. ABB has been able to solve this using the AF platform technology. This allows the performance of the magnet system to be fine-tuned, resulting in an optimized function for the job. it can be used independent of the motor's efficiency class.

For higher locked rotor amp applications such as an IE3 or IE4 motor with a NE or HE design, ABB has successfully designed the 3-pole AF09...AF190 contactors and B6/B7 mini contactors for the AC-3e utilization category.









and control devices

Contact Us @



ABB's AF09...AF190 contactors have been designed with the same rated operational current and rated operational power (up to 690V) for AC-3 and AC-3e utilization category. They are listed below.

		AC-3/AC-3e le/max rated operational current (A) θ ≤ 60 °C													
	AF09	AF12	AF16	AF26	AF30	AF38	AF40	AF52	AF65	AF80	AF96	AF116	AF140	AF146	AF190
220-230-240V	9	12	18	26	33	40	40	53	65	80	96	116	140	146	190
380-400V	9	12	18	26	32	38	40	53	65	80	96	116	140	146	190
415V	9	12	18	26	32	38	40	53	65	80	96	116	140	146	190
440V	9	12	18	26	32	38	40	53	65	80	96	116	140	146	190
500V	9,5	12,5	15	23	28	33	35	45	55	65	80	110	130	130	156
690V	7	9	10,5	17	21	24	25	35	39	49	57	65	80	93	135
1000V <sup>(1)</sup>	-	-	-	-	-	-	-	-	-	25	30	-	-	60/54	85

(1) AF09 ... AF96: AC-3e Ue  $\leq$  690 V

		AC-3/AC-3e													
		Rated operational power (kW) $\theta \le 60 ^{\circ}$ C													
	AF09	AF12	AF16	AF26	AF30	AF38	AF40	AF52	AF65	AF80	AF96	AF116	AF140	AF146	AF190
220-230-240V	2.2	3	4	6.5	9	11	11	15	18.5	22	25	30	37	45	55
380-400V	4	5.5	7.5	11	15	18.5	18.5	22	30	37	45	55	75	75	90
415V	4	5.5	9	11	15	18.5	22	30	37	45	55	55	75	75	90
440V	4	5.5	9	15	18.5	22	22	30	37	45	55	75	90	90	110
500V	5.5	7.5	9	15	18.5	22	22	30	37	45	55	75	90	90	110
690V	5.5	7.5	9	15	18.5	22	22	30	37	45	55	55	75	90	132
1000V <sup>(1)</sup>	-	-	-	-	-	-	-	-	-	35	40	-	-	75	110

(1) AF09 ... AF96: AC-3e Ue ≤ 690 V

### Contactor life cycle durability

Behavior of contactors conducting AC-3 operations in terms of life cycle durability. For AC-3 or AC-3e utilization categories, the electrical durability curves, as available in the catalog, can also be used in IE3/IE4 motors usages. When stating the age of an AC-3 application, the breaking of the rated motor current will have a major influence on the contactor. Since the rated current is lower using an IE3 motor, the life cycle will have a close to the previous durability.



18 / 31

• Selecting the right combination of protection • Softstarters with premium-efficiency motors and control devices

Contact Us @



### Softstarters with premium-efficiency motors

The utilization category that applies to softstarters is AC-53, and due to the switching technology of the softstarter the same category applies regardless of the motor efficiency level. However, when designing a motor control circuit it's important to understand the effects of a premium-efficiency motor.

The softstarter enables a motor to be accelerated smoothly within the desired time, thereby reducing the starting current. After the starting process and reaching the rated speed, the softstarter is usually bypassed, the motor is then directly connected to the grid. Likewise, the motor can be stopped for a preset time. Softstarter is thus ideal for starting and stopping applications, where the inrush current is disproportionately high, as required in some IE3/IE4 motor applications.

The mentioned problems can easily be resolved with a standard softstarter from ABB. The control algorithm and the thyristor technology reduce the inrush and locked rotor current to significantly lower levels and allow for a fully controlled start without issues. The softstarter also makes the whole operation smoother without jerks or shocks during the ramp, extending the lifetime of the mechanical parts and the load that the motor is controlling.

To avoid issues with IE3/IE4 motors, the softstarter power components need to be designed for these types of higher starting currents. ABB's softstarters are designed and built with one of the highest-rated components making all motor starting easy and effective.









## Coordination

ABB's Selected Optimized Coordination tool (SOC) allows the required protection against shortcircuits and overloads to be selected. SOC includes many possible selection choices such as starter type, short-circuit level and overload characteristics, rated power and voltage, motor efficiency class, and so on.

The coordination among devices cannot be determined directly. Tests in power laboratories shall be carried out to qualify the coordination type at low fault and high fault currents, according to UL or IEC standards. ABB's coordination tables are the results of such tests and represent ABB's offerings in terms of motor starting and protection, selectivity, back-up, and switch-disconnector protection.

Determining the Short-Circuit Current Rating of a complete electrical panel can be very challenging, especially if proper considerations are not made during the initial stages of the component selection process.

For IEC, the motor efficiency class now includes how the motor design type use is distinguished.

• IE1/IE2/IE3/IE4 N/H : The asynchronous IE1/IE2/IE3/IE4 motor may be of design N or H, according to standard IEC60034-12:2016.

The selection of a recommended coordinated starter combination according to the AC-3 utilization category does not change when upgrading from an IE1/IE2 motor to an IE3 or IE4 motor.

 IE3/IE4 NE/HE: The asynchronous IE3/IE4 motor may be of design NE or HE, according to standard IEC60034-12:2016 with extended/locked rotor apparent power and current than design N and H motors. The selection of a recommended coordinated starter combination according to the AC-3e utilization category was updated to match the requirements as stated in IEC 60947-4-1 Ed. 4.

or UL selection			Motor efficiency class and design type A		S - Application values - - -		ihort-circuit protection devices Air circuit breaker Fuses « gG » or « aM » Moulded case circuit breaker Manual motor starter			
C - Lefected ( tandard:	Optimized ( Startin (*) Nor	Coordination Mi	otor protection Selectivi Motor Efficiency	ty Back-up Other Devices prote Class - Design: 2/163/164 - 11/H 〇 163/164 - 116/H	ction E			Table stat	tes: Active () Legacy	
Starter Type Direct-on-line si Star-Delta start Soft starter (in S Soft starter (ins	tarter er Line) ride Delta)	Rated voltage	Motor 230 V AC 400 V AC 415 V AC 440 V AC	Rated Power Short- 0.06 km 0.09 km 0.12 km 0.25 km 0.25 km	Circuit Current Ca 12 kA 16 kA 20 kA 20 kA	condination type C Type 1 C Type 2	Protection device Air circuit-breaker Switch fuse Molded case circuit-breaker Manual motor starter	Overload pro Embedded Thermal overl Electronic over Universal mot	tection oad relay A rioad relay or controller	
1		~	500 V AC ¥	0.37 kw ¥	35 kA ¥		~	× .	T ĭ	
647 Coordinati	ion tables four	ad and a second s			*		Expert Por	PDF Books	C Reset filters	
1. Hansal means Hotor Rated an	ad Current	AC, 50 kA, Direct-on-fine st	arter, Coordination type IEC Typ Protection device	e Z. Overland protection. Einbedded, Hotor	Efficiency Class - Design - BEL/BH NE, Contactor	4.	Overload protection	Her allowed	Table	
E DS NV	(PLA) 0.35 A	MS132-0.4	B A	0.25 - 0.4 A	AFOD		Intestind	Ead current E 4 A		
- Pearland Inc.		THE, BE SAL CREATE OF BOARD	Protection device	a Contract production to be added and the or	Contactory	the object (second)	Contribut protection		Table	
Hutor Rated at	ed Currett							Plac allowed		
Poster	(71.4)	Type	Ireal Trip. Carrorei	Current range	Yypus			four current	atus 10	
0.06 NW		H8531-0.25		0.16 - 0.73 A	AF09		Enterlied	A 61.0	17-18 (3*28) ···	
3 Harval me or	starter, 600 Y	AC. MAA Direct-on-fine at	terter, Coordination type. IEC Typ	as Z. Overland protection. Embedded, Mator	Differency Class - Design: HEL/HE2/HE3	E4 16/51 (HE5134)				
House			Protection device		Contactor		Overload protection		Table	
Hotor Rated	and Current							Has allowed		
Power	(FLA)	Type	Inval, Trip, Currents	Current range	Type		Protocological Sector S	head current	tatus ID	
				0.10 - 0.10 #	10.04		1-11-11-11-1			
4 Hanual marries	starter, 400 V	AC 35 KA Direct-on-line at	tartes. Coordination type. IEC Typ	ee Z. Overland protection. Embedded, Matar	Efficiency Dass - Davign HD/H2/HD	10.4 HUML (HISSINF-A)				
Harris			Protection device		Contactor		Overload protection		Table	
Hotor Rated at	ad Currett							Has allowed		
Person	(FLA)	Type batton or	Inst. Trip. Current	Current range	Type		Testaddad	load current	tatus 10	
0.00 100					~				and the second	
S. Manual municipal	ratarter, 400 t	AC. 16 KA. Direct-on-Bost at	tarter, Coordination type 45C Typ	as 2. Overhead protection. Embedded, Honor	Efficiency Data - Design HEL/HE2/HE3	E4 11/14 (14540368539452)	6A5.00			
140.00			Protection device		Centactor		Overload protection		Table	
Hotor Rated at	ad Current							Max advoced		
Paparet	(PLA)	Types	Inot. Trip. Current	Customi range	Type			load current	sature 10	
0.0410				0.10-0.00 %	Pasana					
6 Harrual me to	starter, 400 t	AC, 25 MA, Direct on-line et	tarter, Coordination type IEC Typ	pe Z. Overland protection. Embedded, Hotor	Dificiency Dass - Design. HEL/HE2/HE3	1E4 N/N (H54005H52H52	64.01)			
House			Protection device		Contactor		Overload protection		Table 🗸	
Monte Banadi an	ad Corears							Max offersard		
1				<b></b>		i i			1	
Starter type - Direct-on-line - Start Delta - Soft starter (in line) - Soft starter (inside Delta)			Coordination proposals as well alternatives		Coordination type acc. to IEC - IEC type 1 or type 2		IEC Overloa - Embe soft s - Therr - Electr	Overload relays - Embedded : manual motor st soft starter - Thermal overload relay - Electronic overload relay		





## Marketing material and web

To find the coordination tables for motor protection, please see:





https://www.lowvoltage-tools.abb.com/soc

Stay updated on manual motor starters, contactors and motor protection and control solution.



http://new.abb.com/low-voltage





## Glossary

Ico	Crossover current: current corresponding to the crossover point of the mean or published curves representing the time-current characteristics of the overload relay and the SCPD respectively
Icd	Current representing a fault current equal to or higher than the current corresponding to the crossover point of the mean value of the published curves representing the time-current characteristics of the overload relay and the SCPD respectively
le	Rated operational current according to IEC 60947-1
IE3	Premium-efficiency class for single-speed motors according to IEC 60034-30.
IE4	Super premium-efficiency class for single-speed motors according to IEC 60034-30
l lrc	Locked rotor current, steady-state current with the motor held at rest at rated voltage and frequency
In	Rated current (rating defined in relevant product standard)
Is	Selectivity limit current, current coordinate of the intersection between the total time-current characteristic of the protective device on the load side and the pre- arcing (for fuses) or tripping (for circuit-breakers) time-current characteristic of the other protective device
ls/ln	Starting current ratio
MEPS (Minimum Energy Performance Standard)	Local regulation specifying the minimum required energy performance for energy- using products. In Europe the EU MEPS for direct on-line motors is IE3
Pn	Rated output, the value of the output included in the rating according to IEC 60947-1
RMS	Root Mean Square: The RMS value of an AC supply is the steady DC equivalent, which would convert electrical energy to thermal energy at the same rate in a given resistance
Si	Locked rotor apparent power, apparent power input with the motor held at rest at rated voltage and frequency
SOC	Selected Optimized Coordination tool
SCPD	Short-circuit protective device
Ue	Rated operational voltage according to IEC 60947-4-1





1SBC00223M0201 - 2022.11

**ABB France Electrification Business** Low Voltage Products and Systems 2 rue d'Arsonval F-69687 Chassieu cedex / France

ABB STOTZ-KONTAKT GmbH **Electrification Business** Low Voltage Products and Systems Eppelheimer Straße 82 D-69123 Heidelberg / Germany

ABB AB **Electrification Business** Low Voltage Products and Systems **Protection & Connection** SE-721 61 Västerås / Sweden

You can find the address of your local sales organization on the ABB home page



https://new.abb.com/low-voltage/products/motor-protection



https://new.abb.com/low-voltage

or modify the contents of this document without the subject matter and illustrations contained prior notice. With regard to purchase orders, the therein. Any reproduction, disclosure to third agreed particulars shall prevail. ABB AG does not parties or utilization of its contents - in whole accept any responsibility whatsoever for potential or in parts - is forbidden without prior written errors or possible lack of information in this consent of ABB AG. document.

We reserve the right to make technical changes We reserve all rights in this document and in Copyright © 2023 ABB AG. All rights reserved