

TECHNICAL DATA SHEET

PMA Accessories - SCAK-M - Positioning adapterMetric thread





Positioning adapter for PMA elbow fittings for easy positioning

CE CH

Applications:

• In connection with PMA fittings with metal thread

Features & Benefits:

- Allows easy positioning of elbow connectors with exactly fixation of the outlet direction in a given thread hole
- High fastening torque
- With thread edge protection

Ingress protection:

• IP69 / IP68

Materials

• Nickel-plated brass (other materials e.g. stainless steel available on request)

Compatible with:


PMAFIX Pro, PMAFIX, PMA Smart Line fittings

Environmental properties:

- Free from halogens and cadmium
- RoHS and REACH compliant

Product selection:											
Part no.	Thread size		Dimensions in mm (nom.)							Weight	Packing unit
	metric (thread 1)	metric (thread 2)	g	d1	d2	SW1	SW2	А	С	kg/100 pcs	pcs/PU
SCAK-M20-10	M20x1.5	M20x1.5	10.0	12.5	26.0	24.0	24.0	31.5	11.0	5.6	1
SCAK-M25-11	M25x1.5	M25x1.5	11.0	16.0	32.0	30.0	30.0	35.0	13.0	9.8	1
SCAK-M32-13	M32x1.5	M32x1.5	13.0	22.0	39.0	36.0	36.0	38.0	14.0	13.0	1
SCAK-M40-13	M40x1.5	M40x1.5	13.0	29.0	50.0	46.0	46.0	39.0	14.0	21.8	1
SCAK-M50-14	M50x1.5	M50x1.5	14.0	37.0	59.0	55.0	55.0	41.5	15.0	28.3	1
SCAK-M63-14	M63x1.5	M63x1.5	14.0	47.0	75.0	70.0	70.0	43.0	15.0	50.2	1

 $Our customer service dept. \ or \ local \ distribution \ partner \ will \ be \ pleased \ to \ help \ you \ concerning \ product \ availability \ and \ lead \ time$



Thermal properties:	Value:	Test parameters:	Test method:
Temperature range	− 60 +105°C		PMA DO 9.21-4510

Content of delivery:

- Complete adapter with thread edge protection
- Thread gasket for internal thread
- Flat gasket for external threads (SVN4)
- O-ring

Assembly instructions:

 For the optimal fixation of elbow connectors using SCAK adapters, please use adhesives such as Loctite or similar for threads and consider the listed torques

Allow enough space to screw in elbow connectors. SCAK adapters can thanks to their small outer dimensions be positioned close to each other (e.g. for closely positioned rectangular multi-pin connectors)

Please consider the appropriate assembly instructions on www.pma.ch

