EMEX Mini Space saving & high performance central power supply system



Features and benefits

- True AC/AC 50Hz output
- 1.5kVA rating with 525W for 3 hours, 700W for 2 hours and 1200W for 1 hour
- Ability to use standard proprietary AC distribution and protection devices on outgoing circuits
- Compatibilities with addressable test package using EMEX technology
- Excellent overload capability in full emergency mode
- Excellent recharge capability: 80% after 12-14 hours following rated discharge
- MCB protection throughout no fuses
- Individual MCB protection for AC and DC circuits
- Cooling with on-demand operation (not continuously running)
- Integral maintenance bypass facility (ability to support output load in bypass mode whilst maintenance is performed)
- Maintained output as standard (switchable to non maintained)
- IP21 rate cabinet as standard
- Easy front panel access
- Simple installation
- Dimensions: H:1210 mm x D: 240 mm x W: 610 mm

BS EN 61508 Functional Safety (Safety Integrity Level 2 Certified) KM 673347

L210mm



01 EMEX Mini central power supply system Emex mini specification

| irt no. | ELD8000.015 |
|---|---|
| escription | Static Inverter EMEX Mini 1.5kVA 1-3H SPN |
| ains supply | |
| ltage | 230V to UK standards |
| equency | 50/60Hz |
| ase | 1 phase |
| irrent | 10A Max |
| utput (mains healthy) | |
| ltage | 230V (as supply) |
| wer | 1500VA |
| ase | 1 |
| verter output | |
| ltage | 230V |
| equency | 50/60Hz |
| Iration | 1, 2 or 3 hour(s) |
| łD | < 5% |
| aveform | Sinusoida |
| wer factor range | 0.9 lead to 0.7 lag |
| ase | 1 |
| verter nominal rating | |
| | 1,500 VA |
| attage | 1200W 1 hour |
| attage | 700W 2 hours |
| attage | 525W 3 hours |
| ittery | |
| npere hour | 24 Ah |
| pe | Valve regulated lead acid (VRLA) |
| ysical dimensions | |
| put terminals | 2.5mm |
| utput terminals | 2.5mm |
| ixiliary terminals | 2.5mm |
| binet | 610mm wide x 240mm deep x1210mm tal |
| eight (Including battery) | 166kg Top entry gland plate |
| D indications | |
| ains healthy | |
| ipply from battery (mains failure or fault) | |
| eters | |