



M-M Universal Scheme

This document is intended to describe the components, required inputs and outputs, sequence of operations and the basic logic to implement ABB's transfer scheme for M-M applications.

Contents

M-M Universal Scheme	1
Single Line Diagrams	2
Required Inputs	3
Main 1 Relay	4
Main 2 Relay	4
Required Outputs	5
Main Breaker 1	5
Main Breaker 2	5
Breaker Schematics	5
Main Breaker 1	6
Main Breaker 2	6
The sequence of operations for the ATS scheme would be as follows	7
Selector Switches	7
Initial startup	7
Normal Mode of Operation	8
Electrical interlocks	8
Manual /Maintenance Operation	8
<i>Maintenance of Main 1</i>	8
<i>Maintenance of Main 2</i>	8
<i>Return to Normal</i>	8
Automatic Mode	9
Selector switch device 43 in "Auto", device 43R in "Auto", and device 43T in "Closed"	9
Automatic Mode	9
Selector switch device 43 in "Auto", device 43R in "Auto", and device 43T in "Open"	9
Automatic Mode	10
Selector switch device 43 in "Auto", and device 43R in "Manual"	10

ABB Inc.

ABB

ATS Logic	11
Main 1	11
Close/Open Logic	11
Timers	11
Maintenance	12
Blackout	12
Loss of Source 1	12
Return of Source 1	13
Loss of Source 2	15
Return of Source 2	15
Goose Signals	17
Main 2	18
Close/Open Logic	18
ATS Logic	18
Goose Signals	19
Ethernet Communications	19
HSR	19
PRP	20
Bill of Material	20


Single Line Diagrams

The following is a one line diagram of the connections required to the relays for the implementation of the transfer scheme

ABB Inc.



SINGLE LINE DIAGRAM



Schemes: M-M Universal

Relays: Main 1 Relay Order Code: HAFDDADAFHE5BBN12E
Main 2 Relay Order Code: HAFDDADAFHE5BBN12E


Required Inputs

The following inputs to the each relays being used for the transfer scheme are required for the proper operation of this automatic transfer scheme.

ABB Inc.

ABB

Main 1 Relay



Main 2 Relay





ABB Inc.




Required Outputs

The following outputs from each of the relays being used for the transfer scheme are required for the proper operation of this automatic transfer scheme.

Main Breaker 1




Main Breaker 2



Breaker Schematics

ABB Inc.



Telephone: (954) 752-6700
Telefax: (954) 345-5329



The sequence of operations for the ATS scheme would be as follows

Selector Switches

43 M/A Manual/Auto Switch

Describes manual or automatic operation for the transfer scheme

43R M/A Manual/Auto Restoration Switch

Only when 43 M/A switch is in "Auto", describes if restoration to normal condition would be done manually or automatically

43T C/O Closed or Open Transition Switch

Only when 43 M/A switch is in "Auto" and 43-R M/A is in "Auto", describes if restoration to normal condition would be through an open or closed transition

43P M1/M2 Preferred Switch

When 43 M/A switch is in "Manual", used to indicate what breaker should be opened automatically when all breakers are closed at the same time to perform maintenance operations or to return system to normal when 43R M/A switch is in "Manual"

When 43 M/A switch is in "Automatic" indicates what incoming line is preferred in case both incoming lines are available.

Initial startup

Place selector switch (DEV 43) in 'Manual' mode. Close the preferred main breaker and open alternate main breaker by their respective control switch (DEV CS).

ABB Inc.



Place selector switch in 'Automatic' mode.

Normal Mode of Operation

The normal mode of operation would be with device 43 in “Automatic” mode and preferred main breaker closed.

Electrical interlocks

Under manual operation there is an electrical interlock between all incoming sources to prevent paralleling unless sources are synchronized.

Incoming lines will only be paralleled momentarily as monitored by device 43P. Please refer to manual/maintenance operations.

Under automatic operation it would only be possible to parallel de resources momentarily if device 43T is in “Closed” and the lines are synchronized.

Manual /Maintenance Operation

It would be possible to perform maintenance to any of the incoming lines. Dev 43 shall be in “Manual”. Device 43P will indicate what breaker will stay close if both Main breakers are closed at the same time under manual operation.

Maintenance of Main 1

Device 43P shall be placed on “Main 2” and device 43 shall be placed in “Manual”.

To perform maintenance on Main 1, close both incoming lines subject to electrical interlock above described. Once both incoming breakers are closed, the Main 1 will be open automatically.

Maintenance of Main 2

Device 43P shall be placed on “Main 1” and device 43 shall be placed in “Manual”.

To perform maintenance on Main 2, close both incoming lines subject to electrical interlock above described. Once both incoming breakers are closed, the Main 2 will be open automatically.

Return to Normal

To return the system to normal conditions with preferred main breaker closed and alternate main breaker open. With device 43 in “Manual” mode, place device 43P on preferred main breaker, and then close the

ABB Inc.



opened incoming line subject to electrical above. As soon as the opened incoming line is closed and both incoming breakers are closed at the same time, the alternate main will be open automatically.

Automatic Mode

Selector switch device 43 in “Auto”, device 43R in “Auto”, and device 43T in “Closed”

(a)

Loss of voltage (UV or NEG SEQ) on preferred incoming line will after a time delay cause its main breaker to open and then the alternate breaker will close, provided that voltage is present on the alternate incoming line.

When the voltage is restored to the preferred line, the preferred main breaker would after a time delay automatically close and then the alternate breaker will open.

(b)

However, if the voltage is subsequently lost on the second line after the transfer has occurred as described in (a) above, the second line will after a time delay open.

Return of voltage to the preferred line first will after a time delay cause its main breaker to close, returning the system back to normal.

Return of voltage to the alternate line first will after a time delay cause its main breaker to close. When voltage returns to the preferred line, the preferred breaker will after a time delay close, and then the alternate breaker will open, restoring the system to normal.

(c)

Simultaneous loss (or restoration) of both sources will after a time delay cause the preferred main breaker to open (or close), leaving the alternate breaker open.

Automatic Mode

Selector switch device 43 in “Auto”, device 43R in “Auto”, and device 43T in “Open”

(a)

Loss of voltage (UV or NEG SEQ) on preferred incoming line will after a time delay cause its main breaker to open and then the alternate breaker will close, provided that voltage is present on the alternate incoming line.

When the voltage is restored to the preferred line, the alternate main breaker would after a time delay automatically open and then the preferred breaker will close.

(b)

However, if the voltage is subsequently lost on the second line after the transfer has occurred as described in (a) above, the second line will after a time delay open.

ABB Inc.



Return of voltage to the preferred line first will after a time delay cause its main breaker to close, returning the system back to normal.

Return of voltage to the alternate line first will after a time delay cause its main breaker to close. When voltage returns to the preferred line, the alternate breaker will after a time delay open, and then the preferred breaker will close, restoring the system to normal.

(c)

Simultaneous loss (or restoration) of both sources will after a time delay cause the preferred main breaker to open (or close), leaving the alternate breaker open.

Automatic Mode

Selector switch device 43 in “Auto”, and device 43R in “Manual”

(a)

Loss of voltage of the preferred incoming line will, after a time delay, causes its main breaker to open and then the alternate breaker will close provided that voltage is present on the alternate incoming line.

When the voltage is restored, the system will be restored to normal operation manually. Refer to manual/maintenance operation.

However, if while waiting for manual restoration, the incoming line powering the load loses power, the failed incoming line will open and then the healthy incoming line will close provided that it has been healthy for the specified time

(b)

However, if the voltage is subsequently lost on the second line after the transfer has occurred as described in (a) above, the second line will stay close.

Return of voltage to the open incoming line first will cause, the closed incoming line to open and then the open incoming line will close.

Return of voltage to the closed incoming line first will not cause any operation leaving the closed incoming line close and the open incoming line open.

Simultaneous restoration of both sources will not cause any operation leaving the closed incoming line close and the open incoming line open.

(c)

Simultaneous loss of both sources will not cause any operation, leaving the preferred incoming line closed and alternate breaker open.

(d)

ABB Inc.




Simultaneous restoration of both sources, after both sources were lost at the same time will not cause any operation, leaving the preferred incoming line closed and alternate breaker open.

ATS Logic

The following logic describes what it has been implemented within each of the protective to perform the sequence of operation, as described under the sequence of operation section

Main 1

Close/Open Logic



Timers





ABB Inc.

ABB

Maintenance



Blackout



Loss of Source 1





ABB Inc.

ABB



Return of Source 1




ABB Inc.

ABB





ABB Inc.

ABB

Loss of Source 2



Return of Source 2




ABB Inc.

ABB




ABB Inc.



Goose Signals





ABB Inc.

ABB

Main 2

Close/Open Logic



ATS Logic





ABB Inc.

ABB

Goose Signals




Ethernet Communications

The following schemes represents the preferred communications between relays to transmit GOOSE signals and to ensure that reliable communications exist for the implementation of the transfer scheme


HSR

ABB Inc.

ABB



PRP



Bill of Material

ABB Inc.



43 M/A Manual/Auto switch

43R M/A Manual/Auto Re-transfer switch

43T C/O Close or Open Transition switch

43P M1/M2 Preferred/Maintenance switch

(2) Lockout Relays

(2) REF615 Ordering Code: HAFDDADAFHE5BBN12E for the Mains

(1) Ethernet Switch

ABB Inc.