



M-T-T-M Close Transition

This document is intended to describe the components, required inputs and outputs, sequence of operations and the basic logic to implement ABB's transfer scheme for M-T-T-M applications.

Contents

| | |
|---|----|
| M-T-T-M Close Transition | 1 |
| Single Line Diagrams | 2 |
| Required Inputs..... | 3 |
| Main 1 Relay | 3 |
| Main 2 Relay | 4 |
| Tie Relay..... | 4 |
| Required Outputs..... | 5 |
| Main Breaker 1..... | 5 |
| Main Breaker 2..... | 6 |
| Tie Breakers | 6 |
| Breaker Schematics..... | 7 |
| Main Breaker 1..... | 7 |
| Main Breaker 2..... | 8 |
| Tie Breaker 1..... | 9 |
| Tie Breaker 2..... | 10 |
| The sequence of operations for the ATS scheme would be as follows..... | 10 |
| Selector Switches | 10 |
| Normal Mode of Operation | 11 |
| Electrical interlocks | 11 |
| Automatic Mode | 11 |
| Selector switch device 43 in "Auto" | 11 |
| ATS Logic..... | 12 |
| Main 1 | 12 |
| Close/Open Logic | 12 |
| ATS Logic..... | 12 |
| Goose Signals | 13 |

ABB Inc.

ABB

| | |
|--------------------------------------|-----------|
| Main 2..... | 14 |
| Close/Open Logic | 14 |
| ATS Logic..... | 14 |
| Goose Signals..... | 15 |
| Tie..... | 16 |
| Close/Open Logic | 16 |
| Tie Breaker 1 | 16 |
| Tie Breaker 2..... | 16 |
| Blackout | 16 |
| Loss of Source 1 | 17 |
| Return of Source 1 | 18 |
| Loss of Source 2 | 18 |
| Return of Source 2 | 19 |
| Goose Signals | 20 |
| Ethernet Communications | 21 |
| HSR | 22 |
| PRP | 22 |
| Bill of Material..... | 23 |


Single Line Diagrams

The following is a one line diagram of the connections required to the relays for the implementation of the transfer scheme

ABB Inc.

ABB

SINGLE LINE DIAGRAM



Schemes: M-T-T-M Closed Transition

Relays: Main 1 Relay Order Code: HAFDDADAFHESBBN12E
 Main 2 Relay Order Code: HAFDDADAFHESBBN12E
 Tie Relay Order Code: HAFFFAFAFHESBBN12E


Required Inputs

The following inputs to the each relays being used for the transfer scheme are required for the proper operation of this automatic transfer scheme.


Main 1 Relay

ABB Inc.

ABB




Main 2 Relay



Tie Relay

ABB Inc.

ABB




Required Outputs

The following outputs from each of the relays being used for the transfer scheme are required for the proper operation of this automatic transfer scheme.


Main Breaker 1

ABB Inc.

ABB




Main Breaker 2



Tie Breakers

ABB Inc.

ABB




Breaker Schematics

The following breaker schematics represent all the connections and electrical interlocks required for the proper operation of the Automatic Transfer Scheme

Main Breaker 1

ABB Inc.


ABB



Main Breaker 2

ABB Inc.

ABB



Tie Breaker 1





ABB Inc.

ABB

Tie Breaker 2



The sequence of operations for the ATS scheme would be as follows

Selector Switches

43 M/A Manual/Auto Switch

Describes manual or automatic operation for the transfer scheme

43PT T1/T2 Preferred Tie Switch

ABB Inc.

ABB

Only when 43 M/A switch is in "Auto", used to indicate what tie breaker should be normally open when system is in "Auto" and both incoming lines are available

Normal Mode of Operation

The normal mode of operation would be with device 43 M/A switch in "Auto" mode, both incoming lines will be normally closed, and preferred tie breaker will be open as indicated by 43-PT switch. The alternate (non-preferred) tie breaker shall always be closed when 43 M/A switch is in "Auto" in order for the Automatic Transfer Scheme to work properly.

Electrical interlocks

Under manual operation there is an electrical interlock between all incoming sources to prevent paralleling.

Under automatic operation it would only be possible to parallel the incoming sources momentarily if the lines are synchronized.

Automatic Mode

In order for any of the Automatic mode described in this section to work properly, please make sure that the preferred tie breaker is open as indicated by selector switch 43PT, and the non-preferred tie breaker is always closed.

Selector switch device 43 in "Auto"

(a)

Loss of voltage (UV or NEG SEQ) on either incoming line will after a time delay cause its main breaker to open and then the preferred tie breaker will close, provided that voltage is present on the other incoming line.

When the voltage is restored, the main breaker would after a time delay automatically close and then the tie preferred breaker will open.

(b)

However, if the voltage is subsequently lost on the second line after the transfer has occurred as described in (a) above, the second line will after a time delay open and then the preferred tie would open.

Return of voltage on either line will after a time delay cause its main breaker to close, and then the preferred tie would close. When voltage returns to the other line, the main breaker will after a time delay close, and then the preferred tie breaker will open, restoring the system to normal.

ABB Inc.

ABB

(c)


Simultaneous loss (or restoration) of both sources will after a time delay cause both main breakers to open (or close), leaving the preferred tie breaker open.

ATS Logic

The following logic describes what it has been implemented within each of the protective to perform the sequence of operation, as described under the sequence of operation section

Main 1


Close/Open Logic



ATS Logic

ABB Inc.

ABB



Goose Signals




ABB Inc.


ABB

GOOSE Outputs



Main 2


Close/Open Logic



ATS Logic

ABB Inc.

ABB



Goose Signals





ABB Inc.


ABB




Tie

Close/Open Logic

Tie Breaker 1




Tie Breaker 2



Blackout

ABB Inc.

ABB



Loss of Source 1






ABB Inc.


ABB



Return of Source 1




Note: Applies for Return of either Source (1 or 2)



Note: Applies for Return of either Source (1 or 2)

- BLACKOUT -


(Return of Source 1 after Blackout)



Loss of Source 2

ABB Inc.

ABB




Return of Source 2

ABB Inc.

ABB

- CLOSED TRANSITON -



Note: See 'RETURN_OF_SOURCE_1' tab for logic to open TIE1/2
(Condition is for LOSS_OF_SOURCE1/2)

- BLACKOUT -


(Return of Source 2 after Blackout)



Goose Signals

ABB Inc.

ABB




Ethernet Communications

ABB Inc.

ABB

The following schemes represents the preferred communications between relays to transmit GOOSE signals and to ensure that reliable communications exist for the implementation of the transfer scheme


HSR



PRP

ABB Inc.

ABB



Bill of Material

43 M/A Manual/Auto switch

43-PT T1/T2 Preferred Tie Switch

(3) Lockout Relays

(2) REF615 Ordering Code: HAFDDADAFHE5BBN12E for the Mains

(1) REF615 Ordering Code: HAFFFAFHFHE5BBN12E for the Ties

(1) Ethernet Switch

ABB Inc.