

# Exit LED Quickfit®

## Signature exit LED Quickfit less bracket



Image indicative only

### Range

Signature range

### Product group

Exit LED Quickfit®

### Features

- 3 year warranty
- LED technology 100,000 hours lamp life
- Low power consumption and LED light source for reduced operation and maintenance costs
- High temperature NiCad batteries
- Quickfit LED exit 100K sign (PQFLEDS) without mounting bracket
- Designed for upgrading of installed Quickfit® product - retrofit capability; fits into any existing Quickfit mounting bracket
- Supplied complete with diffusers and all pictograph combinations for single or double sided installation



### Standard products

Catalogue no.	Description
PQFLEDS-LB	Quickfit LED exit 100K pictograph less bracket

### Spare parts

Catalogue no.	Description
03-YPMA001	Battery 3 cell NiCad 3.6V 1.6Ah

### Dimensions

Length	Width	Height
379mm	72mm	212mm

### Weight

Model	Weight
Standard	1.4kg

### Construction

Part	Construction
Body	UV/FR ABS body
Diffuser	Opal acrylic

### Light source

Model	Light source
Standard	Multiple LED 1.2W

### Power consumption

Model	Power consumption
Standard	4.0W

### Photometrics

Model	Class	Classification
Standard	C0	D3.2
	C90	D3.2

**Note:** Designed to comply with AS2293 and meet relevant Australian EMC standards

For more information please contact:

**ABB Australia Pty Limited**

Phone: 1300 666 595

Fax: 1300 666 594

E-mail: AU-ABB-Stanilite@abb.com

**[www.stanilite.com.au](http://www.stanilite.com.au)**

**Note:** We reserve the right to make technical changes or modify the contents of this document without prior notice. With regard to purchase orders, the agreed particulars shall prevail. ABB does not accept any responsibility whatsoever for potential errors or possible lack of information in this document.

We reserve all rights in this document and in the subject matter and illustrations contained therein. Any reproduction, disclosure to third parties or utilisation of its contents – in whole or in parts – is forbidden without prior written consent of ABB.

Copyright © 2016 ABB  
All rights reserved