

## SAFETY PRODUCTS

# **Estrong Emergency Stop** Data Sheet

Estong is an emergency stop used to stop unsafe machine function in order to prevent an accident or reduce its consequences.

Comes standard with a stainless steel enclosure and IP69K rating. Option with a LED for status.





## Optimum Interface

## **Robust Design**

Ideally suited for industries that have special demands, such as food processing or the chemical industry.



## Continuous operation

## **LED Diagnostics**

Models with integrated LED diagnostics reduce downtime when troubleshooting.

**Reliable in extreme conditions** IP69K rating and stainless steel enclosure.



Safety and Protection

## Special Lid Mechanism

Contacts inside the Estrong go into an open or safe state if the cover is not secured properly to the enclosure.

#### Ordering Information

Description	Material Housing	Order code
Estrong, ½ NPT	Stainless Steel	2TLA050220R1020
Estrong, ½ NPT, with protection shroud	Stainless Steel	2TLA050220R1422
Estrong, ½ NPT, 24VDC LED	Stainless Steel	2TLA050220R1222
Estrong, ½ NPT, 115VAC LED	Stainless Steel	2TLA050220R1223
Estrong, ½ NPT, 230VAC LED	Stainless Steel	2TLA050220R1224

NOTE: Anything in **bold** is typically stocked.

 Accessories

Description	Material Housing	Order code
1/2 NPT Cable Gland	Stainless Steel	2TLA050040R0001

NOTE: Anything in **bold** is typically stocked.

Additional information can be found in the Estrong Product Manual.

Technical Data	
Manufacturer	
Address	ABB Electrification Sweden AB / JOKAB SAFETY
	Varlabergsvägen 11
	SE-434 39 Kungsbacka
	Sweden
Electrical characteristics	
Contact type	IEC/EN60947-5-1 double break typ Zb
Contact material	Silver
Termination	Clamp up to 2,5 mm2 Conductors
Utilization category	AC15 A300 3A 240VAC 3A/120VAC 6A/24VDC 2.5A induc
	tive
Thermal current (Ith)	10A
Rated insulation/withstand voltages	500 VAC/2500 VAC
Short circuit overload protection	Fuse externally 10 A (FF)
General	
Enclosure classification	IP67, IP69K
Ambient temperature	-25+80°C
Size	See manual
Shock Resistance	15 g 11 ms
Enclosure/Cover	Stainless Steel 316
Size	See manual
Mounting Positions	Any
Mounting Bolts	4 x M4
Torque Settings	Mounting M5 4,0 Nm
	Lid T20 Torx M4 1,5 Nm
	Terminals 1,0 Nm
Conduit Entries	3 x ½ NPT
Vibration	IEC 68-2-6, 10-55 Hz+1 Hz,
	Excursion: 0.35 mm, 1 octave/min
Safety-related characteristic data and Conformity	
Conformity	European Machinery Directive 2006/42/EC
	EN ISO 12100:2010, EN ISO 13850:2008, EN 60204-
	1:2006+A1:2009
	EN 60947-1:2007+A1:2011, EN 60947-5-1:2004+A1:2009,
	EN 60947-5-5:1997+A1:2005
EN ISO 13849-1	Up to PL e, Cat. 4 depending on system architecture
EN 62061	Up to SIL3 depending on system architecture
Safety data	
Mechanical reliability B10d	1 500,000 operations at 100 mA load
PFHD	<1.0 x 10-7
Proof test interval (life)	21 years
MTTFd	214 years (8 cycles per hour/24 hours per day/365 days
	per year)
Certifications	TÜV, cULus

Information with regard to UL 508

Use 12AWG copper conductors only Electrical Rating: A300 48W5 Type 1 Enclosure Max. Switching Current / Volt / Amp: 120V 6A (720VA break) PF 0.38, 240V 3A (720VA break) PF 0.38

ABB Inc. 305 Gregson Drive Cary, North Carolina 27511 United States electrification.us.abb.com/ products/machine-motor-control We reserve the right to make technical changes or modify the contents of this document without prior notice. With regard to purchase orders, the agreed particulars shall prevail. ABB AG does not accept any responsi-

tice. With regard to purchase orders, the agreed particulars shall prevail. ABB AG does not accept any responsibility whatsoever for potential errors or possible lack of information in this document. We reserve all rights in this document and in the subject matter and illustrations contained therein. Any reproduction, disclosure to third parties or utilization of its contents – in whole or in parts – is forbidden without prior written consent of ABB AG. Copyright© 2022 ABB All rights reserved