## **FurseWELD**

## Cable to cable CC1

Cable to cable CC1 - FurseWELD

	Stranded/solid circular conductor size A (mm²)	Mould part no.	Order code	Powder cartridge part no.	Handle clamp part no.
	16*	CC1-4-16	7TCA083910R1100	32P10	НСРК4
	25	CC1-4-25	7TCA083910R1118	32P10	HCPK4
	35	CC1-4-35	7TCA014980R0050	32P10	НСРК4
	50	CC1-4-50	7TCA083910R1132	45P10	НСРК4
	Ø 8	CC1-4-8SC	7TCA083910R1143	45P10	НСРК4
	70	CC1-4-70	7TCA083910R1134	65P10	НСРК4
	Ø 10	CC1-4-10SC	7TCA083910R1087	65P10	НСРК4
	95	CC1-4-95	7TCA014980R0052	90P10	НСРК4
A	95	CC1-4-95-IU	-	90P10	НСРК4
	120	CC1-4-120	7TCA014980R0049	115P10	НСРК4
	120	CC1-4-120-IU	_	115P10	НСРК4
	150	CC1-4-150	7TCA083910R1096	115P10	НСРК4
	185	CC1-4-185	7TCA083910R1104	150P10	НСРК4
	240	CC1-4-240	7TCA083910R1113	200P10	НСРК4
	300	CC1-4-300	7TCA083910R1122	250P10	НСРК4
	400	CC1-5-400	7TCA083910R1148	2 x 150P10	HCPK5

Special moulds for all FurseWELD products can be manufactured to meet specific customer applications on request  $^{*}2 \times 5103$  Sleeve required when joining conductors  $16 \text{ mm}^2$  or smaller For order codes of powder cartridges and handle clamps, see pages 49-50

FurseWELD moulds should only be used with FurseWELD powders, handle clamps and accessories. If moulds, powders, handle clamps and accessories from other  $manufacturers\ are\ utilized,\ we\ cannot\ guarantee\ the\ safe\ use\ or\ the\ integrity\ of\ the\ completed\ joint$ 

 $Furse WELD\ moulds\ for\ use\ with\ stranded\ conductor\ are\ designed\ for\ use\ with\ non-compacted\ conductor\ to\ BS\ EN\ 60228.\ If\ a\ mould\ for\ compacted\ conductor\ is\ required,$ 

please contact your local representative
Conductors must be installed in the orientation shown to achieve the correct connection