FurseWELD

Cable to cable CC11

Cable to cable CC11 - FurseWELD

| | Stranded/solid circular conductor size A (mm²) | Stranded/solid circular conductor size B (mm²) | Mould part no. | Order code | Powder cartridge part no. | Handle clamp part no. |
|--|--|--|-------------------|-----------------|---------------------------------|-----------------------------|
| | 50 | 50 | CC11-7-5050 | 7TCA083910R1156 | 150P10 | НСРК7 |
| | 70 | 70 | CC11-7-7070 | 7TCA083910R1157 | 200P10 | НСРК7 |
| | 95 | 95 | CC11-7-9595 | 7TCA083910R1160 | 250P10 | НСРК7 |
| | 120 | 120 | CC11-7-120120 | 7TCA014980R0056 | 2 x 150P10 | НСРК7 |
| | 150 | 150 | CC11-8-150150 | 7TCA083910R1161 | 2 x 200P10 | НСРК8 |
| | 185 | 185 | CC11-8-185185 | 7TCA083910R1166 | 2 x 250P10 | НСРК8 |
| | 240 | 240 | CC11-8-240240 | 7TCA083910R1167 | 3 x 200P10 | НСРК8 |
| | 300 | 300 | CC11-8-300300 | 7TCA083910R1169 | 3 x 250P10 | НСРК8 |

Special moulds for all FurseWELD products can be manufactured to meet specific customer applications on request

For order codes of powder cartridges and handle clamps, see pages 49-50

 $Furse WELD\ moulds\ should\ only\ be\ used\ with\ Furse WELD\ powders,\ handle\ clamps\ and\ accessories.\ If\ moulds,\ powders,\ handle\ clamps\ and\ accessories\ from\ other\ powders,\ handle\ powders,\ powder$ $manufacturers \ are \ utilized, we \ cannot \ guarantee \ the \ safe \ use \ or \ the \ integrity \ of \ the \ completed \ joint$

FurseWELD moulds for use with stranded conductor are designed for use with non-compacted conductor to BS EN 60228. If a mould for compacted conductor is required, please contact your local representative

Conductors must be installed in the orientation shown to achieve the correct connection