

# Exit LED Quickfit® Signature exit LED Quickfit frame only Nexus®



Image indicative only

## Range

Signature range

## Product group

Exit LED Quickfit®

## Features

- 3 year warranty
- Features LED technology 100,000 hours lamp life and advanced pulsetime dual rate battery charger with high temperature NiCad batteries
- Low power consumption and LED light source for reduced operation and maintenance costs
- Nexus® monitored, either cabled or wireless
- Frame only version of the LED Quickfit exit sign (PQFLED)
- Designed for upgrading of installed Quickfit® product - retrofit capability; fits into any existing Quickfit mounting bracket
- Supplied less mounting bracket and diffusers - the frame will accept existing MQF/PQF diffusers and backplates



## Nexus products

Catalogue no.	Description
PQFNXSLED-FR	LED Quickfit Nexus LX exit frame only
PQFNRFLED-FR	LED Quickfit Nexus RF exit frame only

## Spare parts

Catalogue no.	Description
03-01218	Battery 4 cell NiCad 4.8V 1.8Ah

## Dimensions

Length	Width	Height
379mm	72mm	212mm

## Construction

Part	Construction
Body	UV/FR ABS body

## Light source

Model	Light source
Nexus LX/RF	Multiple LED 1.6W

## Power consumption

Model	Power consumption
Nexus LX/RF	3.9W

## Photometrics

Model	Class	Classification
Nexus LX/RF	C0	D3.2
	C90	D3.2

Note: Designed to comply with AS2293 and meet relevant Australian EMC standards

For more information please contact:

**ABB Australia Pty Limited**

Phone: 1300 666 595

Fax: 1300 666 594

E-mail: AU-ABB-Stanilite@abb.com

**[www.stanilite.com.au](http://www.stanilite.com.au)**

**Note:** We reserve the right to make technical changes or modify the contents of this document without prior notice. With regard to purchase orders, the agreed particulars shall prevail. ABB does not accept any responsibility whatsoever for potential errors or possible lack of information in this document.

We reserve all rights in this document and in the subject matter and illustrations contained therein. Any reproduction, disclosure to third parties or utilisation of its contents – in whole or in parts – is forbidden without prior written consent of ABB.

Copyright © 2016 ABB  
All rights reserved